

Datasheet

Model Number : R-WR15-1F

Waveguide to Coaxial Adapter

Right Angle, 49.8-75.8 GHz, WR15 to 1.0mm female

Specifications

Frequency Range	49.8-75.8 GHz
Waveguide Type	WR15
Flange Type	FUGP620
RF Connector	1.0mm-Female
VSWR	1.6 max
Insertion Loss	1.0dB max
Material	Copper
Surface Finishing	Gold Plating
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

