

Datasheet

Model Number : R-WR12-1F

Waveguide to Coaxial Adapter

Right Angle, 60~90 GHz, WR12 to 1.0mm female

Specifications

Frequency Range	60-90 GHz
Waveguide Type	WR12
Flange Type	FUGP740
RF Connector	1.0mm-Female
VSWR	1.6 max
Insertion Loss	1.2dB max
Material	Copper
Surface Finishing	Gold Plating
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

