

## Datasheet

Model Number : E-WR10-1F

# Waveguide to Coaxial Adapter

## End Launch, 75~110 GHz, WR10 to 1.0mm-Female

### Specifications

Frequency Range	75-110 GHz
Waveguide Type	WR10
Flange Type	FUGP900
RF Connector	1.0mm-Female
VSWR	1.5 max
Insertion Loss	1.3dB max
Material	Copper
Surface Finishing	Gold Plating
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

