

Datasheet

Model Number : E-WR12-1F

Waveguide to Coaxial Adapter

End Launch, 60.5~91.9 GHz, WR12 to 1.0mm-Female

Specifications

Frequency Range	60.5-91.9 GHz
Waveguide Type	WR12
Flange Type	FUGP740/(UG387/U)
RF Connector	1.0mm-Female
VSWR	1.6 max
Insertion Loss	0.5dB max
Material	Copper
Surface Finishing	Gold Plating
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

