

## Datasheet

Model Number : E-WR34-SF

# Waveguide to Coaxial Adapter

## End Launch, 21.7-33.0 GHz, WR34 to SMA-Female

### Specifications

Frequency Range	21.7-33.0 GHz
Waveguide Type	WR34
Flange Type	FBP260 (Cover)
RF Connector	SMA-Female
VSWR	1.5 max
Material	Copper/Brass
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

### Outline Drawings [mm]:

