

Datasheet

Model Number : E-WR34-2F

Waveguide to Coaxial Adapter

End Launch, 21.7-33.0 GHz, WR34 to 2.4mm-Female

Specifications

Frequency Range	21.7-33.0 GHz
Waveguide Type	WR34
Flange Type	FBP260 (Cover)
RF Connector	2.4mm-Female
VSWR	1.35 max
Material	Copper/Brass
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

