

## Datasheet

Model Number : R-WR22-2F

# Waveguide to Coaxial Adapter

## Right Angle, 33~50 GHz, WR22 to 2.4mm-Female

### Specifications

|                   |                |
|-------------------|----------------|
| Frequency Range   | 33-50 GHz      |
| Waveguide Type    | WR22           |
| Flange Type       | FUGP400        |
| RF Connector      | 2.4mm-Female   |
| VSWR              | 1.6 max        |
| Insertion Loss    | 0.5dB max      |
| Material          | Copper/Brass   |
| Surface Finishing | Gold Plating   |
| RoHS Status       | RoHS Compliant |

### Outline Drawings [mm]:

