

Datasheet

Model Number : R-WR51-SF

Waveguide to Coaxial Adapter

Right Angle, 14.5~22.0 GHz, WR51 to SMA-Female

Specifications

Frequency Range	14.5-22.0 GHz
Waveguide Type	WR51
Flange Type	FBP180 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Insertion Loss	0.3dB max
Material	Copper
Inside Finishing	Silver Plating
Outside Finishing	Anti-Corrosive Grey Paint
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

