

## Datasheet

Model Number : R-WR62-SF

# Waveguide to Coaxial Adapter

## Right Angle, 11.9~18.0 GHz, WR62 to SMA-Female

### Specifications

Frequency Range	11.9-18.0 GHz
Waveguide Type	WR62
Flange Type	FBP140 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Insertion Loss	0.2dB max
Temperature Range	-40°C~+70°C
Material	Copper
Inside Finishing	Silver Plating
Outside Finishing	Anti-Corrosive Grey Paint
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

