

Datasheet

Model Number : E-WR62-NF

Waveguide to Coaxial Adapter

End Launch, 11.9~18.0 GHz, WR62 to N-Female

Specifications

Frequency Range	11.9-18.0 GHz
Waveguide Type	WR62
Flange Type	FBP140 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Temperature Range	-40°C~+70°C
Material	Copper/Brass
Inside Finishing	Silver Plating
Outside Finishing	Anti-Corrosive Black Paint
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

