

Datasheet

Model Number : E-WR75-NF

Waveguide to Coaxial Adapter

End Launch, 9.85~15.0 GHz, WR75 to N-Female

Specifications

Frequency Range	9.85-15.0 GHz
Waveguide Type	WR75
Flange Type	FBP120 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

