

Datasheet

Model Number : R-WR75-NF

Waveguide to Coaxial Adapter

Right Angle, 9.85~15.0 GHz, WR75 to N-Female

Specifications

Frequency Range	9.85-15.0 GHz
Waveguide Type	WR75
Flange Type	FBP120 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Insertion Loss	0.3dB max
Material	Copper/Brass
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

