

Datasheet

Model Number : R-WR90-SF

Waveguide to Coaxial Adapter

Right Angle, 8.2~12.5 GHz, WR90 to SMA-Female

Specifications

Frequency Range	8.2-12.5 GHz
Waveguide Type	WR90
Flange Type	FBP100 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Insertion Loss	0.2dB max
Material	Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black/Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

