

## Datasheet

Model Number : E-WR137-NF

# Waveguide to Coaxial Adapter

## End Launch, 5.9~8.2 GHz, WR137 to N-Female

### Specifications

Frequency Range	5.9-8.2 GHz
Waveguide Type	WR137
Flange Type	FDP70 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black/Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

