

Datasheet

Model Number : E-WR137-SF

Waveguide to Coaxial Adapter

End Launch, 5.38~8.17 GHz, WR137 to SMA-Female

Specifications

Frequency Range	5.38-8.17 GHz
Waveguide Type	WR137
Flange Type	FDP70 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Material	Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black/Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

