

Datasheet

Model Number : E-WR187-SF

Waveguide to Coaxial Adapter

End Launch, 3.94~5.99 GHz, WR187 to SMA-Female

Specifications

Frequency Range	3.94-5.99 GHz
Waveguide Type	WR187
Flange Type	FDP48 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

