

Datasheet

Model Number : R-WR1150-NF

Waveguide to Coaxial Adapter

Right Angle, 0.64~0.98 GHz, WR1150 to N-Female

Specifications

Frequency Range	0.64-0.98 GHz
Waveguide Type	WR1150
Flange Type	FDP8 (Cover)
RF Connector	N-Female
VSWR	1.3 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey/Black Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

