

## Datasheet

Model Number : E-WR28-KM

# Waveguide to Coaxial Adapter

## End Launch, 26.5-40.0 GHz, WR28 to 2.92mm-Male

### Specifications

Frequency Range	26.5-40.0 GHz
Waveguide Type	WR28
Flange Type	UG599/U
RF Connector	2.92mm-Male
Power Handling	20W CW
Insertion Loss	0.35dB typ / 0.5dB max
Return Loss	17dB typ / 15dB min
Surface Finishing	Gold Plating
Weight	9.5g
Temperature Range	-40°C~+85°C
RoHS Status	RoHS Compliant

### Outline Drawings [mm]:

