

Datasheet

Model Number : E-WRD650-SF

Double Ridge Waveguide to Coaxial Adapter End Launch, 6.5~18GHz, WRD650 to SMA(f)

Specifications

Frequency Range	6.5-18 GHz
VSWR	1.5 Max.
Insertion Loss	0.5dB Max.
Flange	FPWRD650
RF Connector	SMA-Female
Impedance	50 Ohms
Power Handling	50W
Material	Copper
Surface Finishing	Grey Paint
RoHS Status	RoHS Compliant

Outline Drawing [mm]:

