

Datasheet

Model Number : E-WR28-KFA

Waveguide to Coaxial Adapter

End Launch, 26.5-40.0 GHz, WR28 to 2.92mm-Female

Specifications

Frequency Range	26.5-40.0 GHz
Waveguide Type	WR28
Flange Type	FBP320
RF Connector	2.92mm-Female
Insertion Loss	0.3dB max
VSWR	1.25dB max
Material	Copper/Brass
Surface Finishing	Gold Plating
RoHS Status	RoHS Compliant

Outline Drawings[mm]:

