

Datasheet

Model Number : R-WR10-1FA

Waveguide to Coaxial Adapter

Right Angle, 73.8~112 GHz, WR10 to 1.0mm-Female

Specifications

Frequency Range	73.8-112 GHz
Waveguide Type	WR10/BJ900
Flange Type	FUGP900, Circular
RF Connector	1.0mm-Female
VSWR	1.5 max
Insertion Loss	1.2dB typical
Material	Copper
Surface Finishing	Gold Plated
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings[mm]:

