# XWSA6330-3-10-Y

Rotary Step Attenuator DC~3GHz, 0~10dB/1dB, 2/10W, SMA/N

#### **FEATURES**

- Small Size
- High Accuracy
- High Stability
- Rugged Design

#### **APPLICATIONS**

- Wireless Communication
- Laboratory Test




#### **Electrical Specifications**

| Frequency Range         | DC~3GHz                          |
|-------------------------|----------------------------------|
| Attenuation Range/Steps | 0~10dB in 1dB steps              |
| Attenuation Accuracy    | ±0.5dB                           |
| VSWR                    | 1.3 max.                         |
| Insertion Loss          | 0.5 max.                         |
| Impedance               | 50 Ohms                          |
| Average Power           | 2W or 10W                        |
| Peak Power              | 100 Watts                        |
|                         | (5µs pulse width, 2% duty cycle) |


## **Mechanical Specifications**


| moonamour opcomouncie |                                 |
|-----------------------|---------------------------------|
| Connector             | SMA or N                        |
| Connector Material    | Brass Nickel Plated             |
| Female Pin            | Beryllium Copper, Gold Plated   |
| Housing               | Aluminum, Brass Nickel Plated   |
| Temperature Range     | -20°C∼+85°C                     |
| Weight                | 250g                            |
| Size                  | 63ר30mm exclusive of connectors |
| RoHS Status           | RoHS Compliant                  |
|                       |                                 |

### **Ordering Information**



### Outline Drawings[mm]





- \* XWSA6330-3-10-Y becomes:
  - $10WSA6330-3-10-N, when frequency \ range\ DC \sim 3GHz,\ 0 \sim 10dB\ attenuation\ range\ in\ 1dB\ steps,\ average\ power\ 10W,\ N\ connectors,\ are\ desired.$
- XWSA6330-3-10-Y becomes
  - 2WSA6330-3-10-S, when frequency range DC~3GHz, 0~10dB attenuation range in 1dB steps, average power 2W, SMA connectors, are desired.