

Datasheet

Model Number : R-WR42-2F

Waveguide to Coaxial Adapter

Right Angle, 17.6-26.7 GHz, WR42 to 2.4mm-Female

Specifications

Frequency Range	17.6-26.7 GHz
Waveguide Type	WR42
Flange Type	FBP220(Cover)
RF Connector	2.4mm-Female
VSWR	1.25 max
Material	Copper
Inside Finishing	Silver Plating
Outside Finishing	Anti-Corrosive Grey Paint
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

