

Datasheet

Model Number : E-WR28-2F

Waveguide to Coaxial Adapter

End Launch, 26.5-40.0 GHz, WR28 to 2.4mm-Female

Specifications

Frequency Range	26.5-40.0 GHz
Waveguide Type	WR28
Flange Type	FBP320 (Cover)
RF Connector	2.4mm-Female
VSWR	1.25 max
Material	Copper/Brass
Surface Finishing	Gold Plating
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

