

Datasheet

Model Number : E-WR28-SF

Waveguide to Coaxial Adapter

End Launch, 26.5-40.0 GHz, WR28 to SMA-Female

Specifications

Frequency Range	26.5-40.0 GHz
Waveguide Type	WR28
Flange Type	FBP320 (Cover)
RF Connector	SMA-Female
VSWR	1.5 max
Material	Copper/Brass
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

