

Datasheet

Model Number : E-WR42-SF

Waveguide to Coaxial Adapter

End Launch, 18.0-26.5 GHz, WR42 to SMA-Female

Specifications

Frequency Range	18.0-26.5 GHz
Waveguide Type	WR42
Flange Type	FBP220 (Cover)
RF Connector	SMA-Female
VSWR	1.5 max
Material	Copper/Brass
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

