

Datasheet

Model Number : R-WR12-VF

Waveguide to Coaxial Adapter

Right Angle, 55~65 GHz, WR12 to 1.85mm female

Specifications

Frequency Range	55-65 GHz
Waveguide Type	WR12
Flange Type	FUGP740
RF Connector	1.85mm-Female
VSWR	1.8 max
Material	Copper/Brass
Surface Finishing	Gold Plating
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

