

Datasheet

Model Number : R-WR15-VF

Waveguide to Coaxial Adapter

Right Angle, 50~65 GHz, WR15 to 1.85mm-Female

Specifications

Frequency Range	50-65 GHz
Waveguide Type	WR15
Flange Type	FUGP620
RF Connector	1.85mm-Female
VSWR	1.8 max
Material	Copper
Surface Finishing	Gold Plating
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

