

Datasheet

Model Number : E-WR112-SF

Waveguide to Coaxial Adapter

End Launch, 6.57~9.99 GHz, WR112 to SMA-Female

Specifications

Frequency Range	6.57-9.99 GHz
Waveguide Type	WR112
Flange Type	FBP84 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Material	Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Black/Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

