

Datasheet

Model Number : E-WR159-NF

Waveguide to Coaxial Adapter

End Launch, 4.64~7.05 GHz, WR159 to N-Female

Specifications

| | |
|-------------------|---------------------------|
| Frequency Range | 4.64-7.05 GHz |
| Waveguide Type | WR159 |
| Flange Type | FDP58 (Cover) |
| RF Connector | N-Female |
| VSWR | 1.25 max |
| Material | Copper |
| Inside Finishing | Silver Plating |
| Surface Finishing | Anti-Corrosive Grey Paint |
| Temperature Range | -40°C~+70°C |
| RoHS Status | RoHS Compliant |

Outline Drawings [mm]:

