

Datasheet

Model Number : E-WR159-SF

Waveguide to Coaxial Adapter

End Launch, 4.64~7.05 GHz, WR159 to SMA-Female

Specifications

Frequency Range	4.64-7.05 GHz
Waveguide Type	WR159
Flange Type	FDP58 (Cover)
RF Connector	SMA-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

