

Datasheet

Model Number : R-WR159-NFA

Waveguide to Coaxial Adapter

Right Angle, 4.9~7.05 GHz, WR159 to N-Female

Specifications

Frequency Range	4.9-7.05 GHz
Waveguide Type	WR159
Flange Type	FDP58 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Black/Grey Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

