

## Datasheet

Model Number : R-WR340-NF

# Waveguide to Coaxial Adapter

## Right Angle, 2.17~3.3 GHz, WR340 to N-Female

### Specifications

Frequency Range	2.17-3.3 GHz
Waveguide Type	WR340
Flange Type	FDP26 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

### Outline Drawings [mm]:

