

Datasheet

Model Number : E-WR430-NF

Waveguide to Coaxial Adapter

End Launch, 1.72~2.61 GHz, WR430 to N-Female

Specifications

Frequency Range	1.72-2.61 GHz
Waveguide Type	WR430
Flange Type	FDP22 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey/Black Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

