

Datasheet

Model Number : R-WR650-NF

Waveguide to Coaxial Adapter

Right Angle, 1.13~1.73 GHz, WR650 to N-Female

Specifications

Frequency Range	1.13-1.73 GHz
Waveguide Type	WR650
Flange Type	FDP14 (Cover)
RF Connector	N-Female
VSWR	1.25 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey/Black Paint
Temperature Range	-30°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

