

## Datasheet

Model Number : R-WR770-NF

# Waveguide to Coaxial Adapter

## Right Angle, 0.96~1.46 GHz, WR770 to N-Female

### Specifications

|                   |                                 |
|-------------------|---------------------------------|
| Frequency Range   | 0.96-1.46 GHz                   |
| Waveguide Type    | WR770                           |
| Flange Type       | FDP12 (Cover)                   |
| RF Connector      | N-Female                        |
| VSWR              | 1.25 max                        |
| Material          | Aluminum                        |
| Inside Finishing  | Chromate Conversion             |
| Surface Finishing | Anti-Corrosive Grey/Black Paint |
| Temperature Range | -30°C~+70°C                     |
| RoHS Status       | RoHS Compliant                  |

### Outline Drawings [mm]:

