

Datasheet

Model Number : R-WR975-NF

Waveguide to Coaxial Adapter

Right Angle, 0.76~1.15 GHz, WR975 to N-Female

Specifications

Frequency Range	0.76-1.15 GHz
Waveguide Type	WR975
Flange Type	FDP9 (Cover)
RF Connector	N-Female
VSWR	1.3 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey/Black Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

