

## Datasheet

Model Number : R-WR1500-NF

# Waveguide to Coaxial Adapter

## Right Angle, 0.49~0.75 GHz, WR1500 to N-Female

### Specifications

Frequency Range	0.49-0.75 GHz
Waveguide Type	WR1500
Flange Type	FDP6 (Cover)
RF Connector	N-Female
VSWR	1.3 max
Material	Aluminum
Inside Finishing	Chromate Conversion
Surface Finishing	Anti-Corrosive Grey/Black Paint
Temperature Range	-40°C~+70°C
RoHS Status	RoHS Compliant

### Outline Drawings [mm]:

