

## Datasheet

Model Number : TWTM112P50W

# Waveguide Medium Power Termination

## WR112, 6.57~9.99 GHz, 50W

### Specifications

Frequency Range	6.57-9.99 GHz
Waveguide Type	WR112
Flange Type	FBP84(Cover)
VSWR	1.25 max
Power Handling(CW)	50W
Temperature Range	-40°C~+70°C
Material	Alloyed Copper
Inside Finishing	Silver Plating
Surface Finishing	Anti-Corrosive Grey/Black Paint
RoHS Status	RoHS Compliant

Outline Drawings [mm]:

