

## Datasheet

Model Number : R-WR42-KF

# Waveguide to Coaxial Adapter, Right Angle

## 17.6~26.7 GHz, WR42 to 2.92mm-Female

### Specifications

Frequency Range	17.6-26.7 GHz
VSWR	1.20 Max.
Flange	FBP220
RF Connector	2.92mm-Female
Impedance	50 Ohms
Material	Brass/Copper
Surface Finishing	Black Paint
RoHS Status	RoHS Compliant

Dimensions [mm]:

