



## Datasheet

Model Number : R-WR28-KFG

# Waveguide to Coaxial Adapter, Right Angle

## 26.3~40 GHz, WR28 to 2.92mm-Female

### Specifications

Frequency Range	26.3-40.0 GHz
Waveguide Type	WR28
Flange Type	FBP320/UBR320 (Cover)
RF Connector	2.92mm-Female
VSWR	1.25 max
Insertion Loss	0.3dB max
Average Power	50W
Material	Copper/Brass
Operating Temperature	-40°C~+70°C
Storage Temperature	-55°C~+85°C
Surface Finishing	Gold Plated
RoHS Status	RoHS Compliant

### Outline Drawings [mm]:

