

Datasheet

Model Number : R-WR28-KF

Waveguide to Coaxial Adapter, Right Angle

26.3~40.0 GHz, WR28 to 2.92mm-Female

Specifications

Frequency Range	26.3-40.0 GHz
VSWR	1.20 Max.
Flange	FBP320
RF Connector	2.92mm-Female
Impedance	50 Ohms
Material	Brass/Copper
Surface Finishing	Black Paint
RoHS Status	RoHS Compliant

Dimensions[mm]:

