

## Datasheet

Model Number : TWTP5P0.5W

# Low Power Waveguide Precision Terminations

## WR5, 145~220GHz, 0.5W

### Specifications

|                    |                          |
|--------------------|--------------------------|
| Frequency Range    | 145-220GHz               |
| Waveguide Type     | WR5(BJ1800)              |
| Flange Type        | FUGP1800 Circular Flange |
| VSWR               | 1.35 max                 |
| Power Handling(CW) | 0.5W@25°C                |
| Temperature Range  | -40°C~+70°C              |
| Material           | Copper                   |
| Finish             | Gold Plated              |
| RoHS Status        | RoHS Compliant           |

Outline Drawings [mm]:

